

Davenport Lift Control

Tel: 02085048286 Fax: 02085048297

Slim Fit LED Kit with Integral Non-Maintained Emergency Light

Part Number: LED22000SE

This unit is compatible for use with the Otis Europa and GEN2 COP panels, providing a much brighter level of illumination than its fluorescent counterpart. It is cheaper to run, offers a much longer life span and is suitable for retro-fit, modernisation and new installation applications. The control unit is pre-wired, offering a simple 'plug and play' format. It also features an integral non-maintained emergency LED light.

Contents:-

1 x power/control unit

2 x 2m (2000mm) of self-adhesive LED strip lighting

1 x ½ m (500mm) of self-adhesive emergency lighting





Installation Instructions.

Remove the existing fluorescent tubes and ballast units, before thoroughly cleaning the entire area where these tubes were situated. This will not only help to maximise the LED brightness, but a clean and dry surface will also optimise adherence of the LED strip.

- · Thoroughly clean the diffusers, which will also help to achieve optimal light levels.
- Remove the protective backing, before placing the LED strip in the space previously occupied by the fluorescent tubes. Also, the LED strip can be cut along the scissor marks.
- The control box can either be fitted where the ballast unit originally was, or on the rear of the COP. The non-maintained emergency LED strip can either be fitted in the COP, alongside the alarm button, or at the top of the COP.
- Ensure that all three LED strips are plugged into the correct sockets and that the mains lead is connected to an existing lighting feed.